



# Reducing manipulations in control simulation experiment based on instability vectors with Lorenz-63 model

Mao Ouyang<sup>1</sup>, Keita Tokuda<sup>2</sup>, and Shunji Kotsuki<sup>1,3,4</sup>

<sup>1</sup>Center for Environmental Remote Sensing (CEReS), Chiba University, 1–33 Yayoi, Inage, Chiba 263–8522, Japan

<sup>2</sup>Department of Computer Science, University of Tsukuba, 1–1–1 Tennodai, Tsukuba, Ibaraki 305–8577, Japan

<sup>3</sup>Institute for Advanced Academic Research (IAAR), Chiba University, 1–33 Yayoi, Inage, Chiba 263–8522, Japan

<sup>4</sup>PRESTO, Japan Science and Technology Agency, 4–1–8 Honcho, Kawaguchi, Saitama 332–0012, Japan

**Correspondence:** Mao Ouyang (ouyang.mao@chiba-u.jp), Shunji Kotsuki (shunji.kotsuki@chiba-u.jp)

**Abstract.** Controlling weather is an outstanding and pioneering challenge for researchers around the world, due to the chaotic features of the complex atmosphere. A control simulation experiment (CSE) on the Lorenz-63 model, which consists of positive and negative regimes represented by the states of variable  $x$ , demonstrated that the variables can be controlled to stay in the target regime by adding perturbations with a constant magnitude to an independent model run (Miyoshi and Sun, 2022). The current study tries to reduce the input manipulation of CSE, including the total control times and magnitudes of perturbations, by investigating how controls affect the instability of systems. For that purpose, we first explore the bred vector (BV) and singular vector (SV), which represent the instability properties of chaotic models without and under control in the Lorenz-63 model. The maximum growth rate of SV shows significant reductions when the variable  $x$  was controlled into the target regime. Subsequently, this research proposes to update the magnitude of perturbations adaptively based on the maximum growth rate of SV; consequently, the times to control will also change. The proposed method successfully reduces around 40% of total control times, and around 20% of total magnitudes of perturbations, compared to the case with constant magnitude. Results of this research suggest that investigating the impacts of control on instability would be beneficial for designing methods to control the complex atmosphere with feasible manipulations.

## 1 Introduction

The ability to control the future based on past and present data is of interest in geophysics, e.g., reducing extreme and rare events, controlling climate changes, and changing cyclone tracks (Lucarini et al., 2016). Miyoshi and Sun (2022) proposed a control simulation experiment (CSE) to change the future based on the ensemble forecasts in an idealised model. Their experiments successfully controlled the state variable  $x$  in the positive regime of the Lorenz-63 model (Lorenz, 1963; Miyoshi and Sun, 2022) and reduced the extreme values by the Lorenz-96 model (Lorenz, 1996; Sun et al., 2022). However, revealing the fundamental principles behind the mechanism of controlling the weather remains obscure, and designing the control approach with feasible manipulations is still challenging. Here, we investigate two types of vectors, namely, bred vector (BV) and singular vector (SV), which are frequently used to explore the instability properties of chaotic models, to try to find feasible manipulations for CSE in the Lorenz-63 model.



Breeding method was proposed to estimate dynamic forecast errors in atmospheric models (Toth and Kalnay, 1993, 1997).  
25 BV represents the nonlinear initial error growth within short- and medium-range periods by minimal computation effort. Zhang et al. (2015) demonstrated that the Lorenz-63 model has two different bred vectors, which would converge to one when a small random noise was added to the perturbations at each breeding cycle (Corazza et al., 2003). Singular vector (SV) was defined as the fastest growing perturbations through singular value decompositions of an operator, e.g., tangent linear model (TLM) (Diaconescu and Laprise, 2012). The initial perturbations in ensemble prediction system at the European Centre for  
30 Medium-Range Weather forecasts (ECMWF) were constructed by SVs, due to which produced dispersive ensembles with the most unstable directions (Palmer, 2019). Kim and Jung (2009) identified the regions sensitive to small perturbations in a tropical cyclone by SV. The growth rates of BV and SV were reported to be able to predict the regime changes in the Lorenz-63 model (Evans et al., 2004; Norwood et al., 2013).

Present study investigates the impacts of control in the Lorenz-63 model on BV and SV and discusses the approach of intro-  
35 ducing these vectors to determine feasible manipulations in CSE. We first review the approach of CSE briefly (Miyoshi and Sun, 2022), and describe the methods for calculating BV and SV. Then, two trajectories of the Lorenz-63 model: one without control, and the other one with control activated at a certain time, are calculated. We compare the BVs and the SVs of the two trajectories at the initial stage of activating control and during a long time period. Based on the features of vectors, we will discuss possible approaches to adaptively determine the manipulations in CSE.

## 40 2 Method

### 2.1 Lorenz-63 model

The model used in this study is Lorenz-63 model, given by:

$$\dot{x} = \sigma(y - x), \tag{1}$$

$$\dot{y} = x(\rho - z) - y, \tag{2}$$

45  $\dot{z} = xy - \beta z, \tag{3}$

where the standard parameters  $\alpha = 10$ ,  $\rho = 28$ , and  $\beta = 8/3$  are selected for chaotic behaviour with two regimes i.e., the famous butterfly pattern (Lorenz, 1963). The initial condition is chosen as  $(x, y, z) = (8.20747939, 10.0860429, 23.86324441)$  following Miyoshi and Sun (2022). Nature run (NR) is obtained by integrating the Lorenz-63 model for 208,000 time steps using the fourth-order Runge-Kutta scheme with the width of each time step ( $dt$ ) equals to 0.01. Hereafter in this paper, we use  
50 the number of these discretised time steps as the time parameters. This trajectory is named as  $x_n$ , where subscript  $n$  represents NR without control.



## 2.2 Control simulation experiment

The CSE is an output feedback control method that determines manipulations based on outputs (or signals) from the system. In Miyoshi and Sun (2022)'s framework, the output is observation data generated from NR. To estimate accurate analysis, the CSE needs to employ sequential data assimilation cycles. This study implements the Ensemble Transform Kalman Filter (ETKF) (Bishop et al., 2001) following Miyoshi and Sun (2022). Three initial forecast ensembles are obtained by adding random Gaussian noise  $r \sim \mathcal{N}(\vec{5}.0, 1.0\mathbf{E})$  to NR (Kalnay et al., 2007), where  $\mathbf{E}$  is the identity matrix,  $\vec{5}.0$  denotes the vector  $(5, 5, 5)^T$ , and  $\mathcal{N}(\vec{5}.0, \Sigma)$  denotes the multivariate normal distribution applied throughout the paper and defined as below:

$$\mathcal{N}(\vec{5}.0, \Sigma) \equiv \frac{1}{(2\pi)^{\frac{3}{2}} |\Sigma|^{\frac{1}{2}}} \exp\left(-\frac{1}{2}(r - \vec{5}.0)^T \Sigma^{-1}(r - \vec{5}.0)\right). \quad (4)$$

Observations are generated every  $T_a = 8$  time steps by adding Gaussian noise  $\mathcal{N}(\vec{0}.0, 2.0\mathbf{E})$  to NR, and are assimilated in the data assimilation cycle. Multiplicative inflation of the ETKF is manually tuned to be 1.04, which is consistent with previous studies (Kalnay et al., 2007). The first 8,000 time steps, corresponding to 1,000 data assimilation cycles, are discarded to ensure that the root mean square error (RMSE) of the mean of ensemble forecast and NR is around 0.30 (Yang et al., 2012). The purpose of the ensemble data assimilation cycle is to obtain ensemble forecasts for determining manipulations in CSE.


The goal of CSE is to control state variable  $x$  to stay in the positive regime by adding perturbations to NR. The process designed by Miyoshi and Sun (2022) is reviewed as follows:

1. Perform a data assimilation based on observations at time  $t$ .
2. Employ an ensemble forecast for  $T$  time steps from  $t$  to  $t + T$ .
3. If at least one ensemble member changes the regime, control (step 4) will be activated; otherwise, data assimilation at time  $t + T_a$  will be performed for the next cycle (step 1).
4. Perturbations are defined as the differences between the ensemble forecasts with and without regime changes. If all three ensemble members show regime change, former initial ensembles will be forecasted for extended time steps to identify at least one ensemble member showing no regime change from  $t$  to  $t + T$ . The perturbations normalized by constant Euclidean norm  $D$  are added to NR at every time step from  $t + 1$  to  $t + T_a - 1$ . The new NR, i.e., NR with adding perturbations, is used to generate observations for subsequent data assimilation cycle (step 1).

The forecast time period  $T$  and Euclidean norm of perturbations  $D$  are tunable parameters in CSE. The ratio of successful control was high when  $T = 300$  time steps and  $D = 0.05$  (Miyoshi and Sun, 2022), thus, we adopt these parameters in this study. The trajectory under control by CSE is named as  $x_c$ , where the subscript  $c$  represents NR under control.

## 2.3 Bred vector

Of the two types of vectors, BV is the easier and faster to be computed. We need to define the trajectory of interest  $x_i$ , which is  $x_n$  or  $x_c$  in this study. Figure 1 (a) shows the method for calculating BV. At the beginning of breeding cycle at time  $t$ , a perturbation  $p$ , scaled to size  $\delta$ , and a Gaussian noise  $r \sim \mathcal{N}(\vec{0}, 0.1\mathbf{E})$  (Corazza et al., 2003), are added to the trajectory  $x_i(t)$ .



**Figure 1.** Methods for calculating (a) BV; and (b) SV. Please refer to the text for the meaning of each parameter.

The initial condition for the perturbed trajectory  $x_p(t)$ , at time  $t$ , will be:

$$x_p(t) = x_i(t) + \delta \frac{p}{\|p\|} + r, \quad (5)$$

85 where  $\|p\|$  is the Euclidean norm of  $p$ . The Lorenz-63 model is then used to integrate the perturbed trajectory forward starting from  $x_p(t)$  for both trajectories without control  $x_n$  and under control  $x_c$ . At the end of the rescaling interval  $T_r$ , BV can be obtained by subtracting  $x_i(t + T_r)$  from the perturbed trajectory,

$$BV(t + T_r) = x_p(t + T_r) - x_i(t + T_r). \quad (6)$$

The process is repeated from Eq. (5) with  $p = BV(t + T_r)$  as the perturbation for the next breeding cycle. The growth rate of  
 90 BV is calculated by  $\frac{1}{T_r} \ln \frac{\|BV\|}{\delta}$ , where  $\|BV\|$  is the Euclidean norm of BV. The main parameters of BV are the perturbation size  $\delta$ , and rescaling interval  $T_r$ , which represent the effects of linear and nonlinear disturbances on error growth. We set  $\delta$  equals to 1.0 and  $T_r$  equals to 8 time steps following Evans et al. (2004). The growth rate of BV is calculated once every  $T_r = 8$  steps when the norm of BV is normalized. To obtain an instantaneous BV growth rate at every time step, we used parallel BVs, each normalized successively at different time points along the trajectory.

95 Here, this study calculated BV of CSE without using any control inputs for the perturbed run. Specifically, the perturbed run  $x_p(t + T_r)$  is the run without control inputs whereas and the trajectory  $x_c(t + T_r)$  is the CSE with control inputs. The necessary control inputs for the perturbed run can be very different from the inputs for the baseline trajectory if we add control inputs for the perturbed run. Therefore, we did not add control inputs for the perturbed run to calculate BV of CSE.

## 2.4 Singular vector

100 The vectors which maximize the growth rate of perturbations for a chosen norm and optimization time interval ( $T_o$ ) can be represented by SV. The process of finding SV for a given state ( $x_n$  or  $x_c$ ) starts with the Jacobian matrix (Diaconescu and Laprise,



2012), which of Lorenz-63 model at a given state  $(x(t), y(t), z(t))$ , is given by

$$\mathbf{J}(t) = \begin{bmatrix} -\sigma & \sigma & 0 \\ \rho - z(t) & -1 & -x(t) \\ y(t) & x(t) & -\beta \end{bmatrix}. \quad (7)$$

Through numerical integration of the Jacobian matrices from time  $t$  to  $t + T_o - 1$ , we can obtain the tangent linear model (TLM), as indicated in Fig. 1 (b):

$$\mathbf{TLM} = \mathbf{J}(t + T_o - 1)\mathbf{J}(t + T_o - 2)\cdots\mathbf{J}(t). \quad (8)$$

Subsequently, SV is calculated through singular value decomposition of TLM, which means that TLM can be decomposed as:

$$\mathbf{TLM} = \mathbf{U}\mathbf{S}\mathbf{V}^T, \quad (9)$$

where  $\mathbf{U}$  and  $\mathbf{V}$  are orthonormal matrices (Press et al., 1992),  $\mathbf{V}^T$  denotes the conjugate transpose of  $\mathbf{V}$ ,  $\mathbf{S} = \text{diag}(s_{11}, s_{22}, \dots, s_{ii}, \dots, s_{nn})$  is a diagonal matrix with descending non-negative singular values. We calculate the first column of  $\mathbf{V}$ , which is the initial leading SV, corresponding to the fastest growing vector from time  $t$  to  $t + T_o$ . Euclidean norm is employed to compute the growth rate of SV, which is given by  $\frac{1}{T_o} \ln s_{ii}$ .


The construction of sequential TLM depends on the trajectory of interest (Fig. 1 (b)), thus, SV is influenced by the time period  $T_o$  (Norwood et al., 2013). In this research, we assume not to use the future data in CSE, and set  $T_o$  equals to 1 time step, i.e., 0.01 time units in the original Lorenz-63 model. The TLM for the trajectories without and under control  $x_c$  are constructed based on the Jacobian matrix of the Lorenz-63 model (Eq. 7), assuming that the manipulations applied in the CSE can be regarded as an external force that would not affect the propagation of perturbations, i.e., Jacobian matrix.

### 3 Results

#### 3.1 Control simulation experiment

We first conduct the experiments to confirm that CSE can control the state variable  $x$  to the target regime. Experimental results without control, i.e., trajectory with orange lines ( $x_n$ ), and under control, i.e., trajectory with magenta lines ( $x_c$ ), are shown in Fig. 2. Spin-up states refers to the initial period taken before the control is activated where the variables might suffer from transit effects (Lorenz, 1996), which are shown as blue lines in Fig. 2. Observation of Figs. 2 (b) and (d) demonstrates that CSE can successfully control the state variable  $x$  in the positive regime.

We calculate BV and SV of the two trajectories,  $x_n$  and  $x_c$ , based on the methods described in Section 2. To investigate the influence of control on the vectors, we focus on the instantaneous changes of vectors when control is activated and the changes of vectors during a long time period, which will be shown subsequently.




**Figure 2.** State variables of the Lorenz 63 model. (a) State variable  $x$  in 2D plane without control. (b) After control, state variable  $x$  stays in the positive regime. (c) Lorenz’s butterfly attractor from NR, i.e., no control ( $x_n$ ). (d) Trajectory under control ( $x_c$ ). Blue line represents the spin-up states. Orange and magenta lines represent the NR without and under control, respectively. Control is activated at time 32.41.

### 3.2 Influence of control at the initial stage

Figure 3 shows the vector changes without and under control at the initial stage of experiments. After discarding the first 8,000  
 130 time steps, we start CSE at the time of 32.41. Figure 3 (a) indicates the time to start control and the different trajectories without and under control by orange lines  $x_n$ , and magenta lines  $x_c$ , respectively. Figures 3 (b) and (c) show changes in BV and SV for experiment without and with control inputs. Even though the trajectory is changed, both the directions and magnitudes of SV are similar for those without and under control (Fig. 3 (c)).

### 3.3 Influence of control during a long time period

135 It was reported that the regime changes of the Lorenz-63 model can be predicted by the growth rates of BV (Evans et al., 2004) and SV (Norwood et al., 2013). In the case of BV, the regime change was predicted by the growth rate, i.e., when the growth rate in current cycle exceeds 0.064, next cycle will change to the other regime (Evans et al., 2004). Norwood et al. (2013)



**Figure 3.** Experimental results of changes in two vectors at the initial stage of CSE. (a) State  $x$  at the initial stage of experiments without and under control. (b) The BVs. (c) The SVs. Blue line represents the spin-up states. Orange and magenta lines represent the NR without and under control, respectively. Control is activated at time 32.41.

**Table 1.** Regime change forecast verification of BV and SV.


	Hits	Misses	False alarms	Threat score
BV	344	43	25	83.5 %
SV	348	34	15	87.7 %

reported that the growth rate of SV also implied the regime changes, i.e., when the growth rate of SV exceeds 0.0296 in current cycle, state variable  $x$  would change to the other regime in the next cycle.

140 Examined vectors of the trajectory without control are shown in Figs. 4 (a) and (b) for 2,500 time steps. Table 1 shows the forecast verifications (Jolliffe and Stephenson, 2011) based on the rules of regime changes prediction described above, where “hit” means the rule successfully forecasts the observation; “miss” means that regime change is observed but not forecasted by the rule; and “false alarm” means that the rule forecasts a regime change but no regime change occurs; “threat score” is an index value focused on hit events, which represents the ratio of the number of hit events to the total number of hit, miss, 145 and false alarm events (Jolliffe and Stephenson, 2011). The threshold values used here are described in the above paragraph. Results indicates that the growth rate of SV shows better performance than BV regarding the regime change prediction.

The features of BV and SV of trajectory under control are shown in Figs. 4 (c) and (d). Characteristics of BV and SV are altered by the control. Even though state  $x$  was controlled in positive regime, BV shows growth rates exceed 0.064 (Fig. 4 (d)). On the other hand, the growth rate of SV is reduced after control, e.g., maximum growth rate shows 5 % decrease, i.e., from 150 0.0312 to 0.0296 (Fig. 4 (e)).





**Figure 4.** Experimental results for long time period. Growth rates of BV (a) without control and (c) under control. Growth rates of SV (b) without control and (d) under control. Control is activated at time 32.41. The black dashed lines are the trajectories of interest,  $x_n$  and  $x_c$ . Coloured stars in (a) and (c) represent the growth rate of BV, with absolute value shown in the colour bar below (d). Coloured stars in (b) and (d) represent the growth rate of SV, with absolute value shown in the colour bar below (e).


## 4 Discussion

Our results demonstrated that controlling the state variables changed the characteristics of BV and SV. Here, we will discuss a new approach which could determine feasible manipulations, including total control times and magnitudes of perturbations in CSE, through the insights from the investigations on instability vectors.

### 155 4.1 Introduce growth rate of SV to update magnitude adaptively

Miyoshi and Sun (2022) controlled the state variables by adding constant magnitude of perturbations to NR in their CSE. The schematic diagram of the process related to manipulation in CSE is shown in Figs. 5 (a-c). After performing the data assimilation at time  $t$ , analysis ensembles are iterated for  $T$  time steps to find the ensemble members with and without regime changes (Fig. 5 (a)), the differences of which during  $t + 1$  and  $t + T_a + 1$  over 0.08 time units are regarded as perturbations






**Figure 5.** Schematic illustrations of the experimental procedures. (a) Determine the ensemble members with and without regime changes. (b) Calculate the perturbations based on the differences of the ensemble forecasts obtained from (a). (c) Rescale the perturbations to magnitude,  $D$ , and add them to NR. (d) Adaptively update the magnitude  $D$  according to the growth rate of SV of analysis mean. Please note that the axes  $x_1$ ,  $x_{n-1}$ , and  $x_n$  in (b), (c), and (d) represent that the perturbations are multidimensional vectors in this study.


160 (Fig. 5 (b)). State variables are changed by adding the rescaled perturbations with constant magnitude  $D$ , to NR from  $t + 1$  to  $t + T_a - 1$  (Fig. 5 (c)). Miyoshi and Sun (2022) suggested that the magnitude of perturbation was a sensitive parameter, and needed further investigations.

Investigation of SV showed that when the state  $x$  was controlled in positive regime, the maximum growth rate of SV was less than 0.0296 (Section 3.3). We then propose to apply this rule in CSE to update the magnitude of perturbations added to  
 165 NR adaptively, as shown in Fig. 5 (d). The perturbations (Fig. 5 (b)) are rescaled with initial Euclidean norm  $D = 0.010$ , and are added to the integration of analysis mean  $\bar{x}_t^a$ , which is the mean value of the analysis ensembles after the data assimilation (step 1 of CSE), from  $t + 1$  to  $t + T_a - 1$ . We calculate the growth rates of SVs for these  $T_a - 1$  time steps. The magnitude  $D$  is determined until the maximum growth rate of SVs was less than 2.96, otherwise increase  $D$  by 0.001. The process will finish after either finding  $D$  which meets the requirement, or  $D$  reaching the boundary which is assumed as the maximum possible  
 170 intervention.

We conduct experiments with only one data assimilation cycle to investigate the applicability of growth rate of SV in CSE. When  $D$  is subjectively determined, Fig. 6 (a) shows that the cases with too small (0.010) and too large (1.400) magnitudes cannot successfully control the state  $x$  in positive regime, whereas, that with magnitude 0.050 can achieve the goal. If  $D$  is determined by the growth rate of SV, Fig. 6 (b) notes that the necessary magnitude to control state  $x$  in positive regime is only  
 175 0.021. This test elaborates that the growth rate of SVs can be applied in CSE to successfully control state variables.



**Figure 6.** Introducing growth rate of SV to control the state variables. (a) Influence of magnitudes on the control in CSE. (b) Introduce growth rate of SV to calculate the necessary magnitudes. The grey dotted lines are the forecast ensembles. Black lines represent the NR before control. Perturbations are added to NR from time 0.01 to 0.07 over 7 time steps. The purple and cyan lines represent the NR after control with constant magnitude of perturbations 0.010 and 1.400, respectively. The red line in (a) represents the NR after control with subjectively determined constant magnitude of perturbation 0.050. The red line in (b) represents the NR after control with magnitude of perturbations determined by growth rate of SV, 0.021.



**Figure 7.** Comparison between constant and adaptive magnitudes in CSE for 500 time steps. (a) Constant magnitude in CSE. (b) Introduce the growth rate of SV to update the magnitudes adaptively. (c) Adaptively update the magnitude by growth rate of SV and boundary. The red lines represent the NRs after control. The thick orange, magenta, and blue lines represent the times to activate control by constant magnitude (a), adaptive magnitude without boundary (b), and adaptive magnitude with boundary (c), respectively.



**Table 2.** Comparison between constant and adaptive magnitudes for 500 time steps.

	The number of control inputs	Total magnitudes
Constant $D$	312	15.6
Adaptive $D$ by growth rate of SV	112	12.9
Adaptive $D$ by growth rate of SV and boundary	259	12.4


## 4.2 Comparison between constant and adaptive magnitudes

To investigate the influence of adaptive magnitude on the total control times and magnitudes of perturbations, we conduct CSEs with constant magnitude, 0.05, as recommended by Miyoshi and Sun (2022), adaptive magnitude without boundary, and adaptive magnitude with boundary to be 0.05, for 500 time steps. The results are shown in Fig. 7 and Table 2. The total control times reduce from 62.4 % (312 out of 500) to 22.4 % (112 out of 500) if the growth rate of SV was implemented to update the magnitude adaptively. The case with adaptive magnitude and boundary shows around 20 % decrease of total magnitudes of perturbations compared to that with constant magnitude.

We conduct 40 experiments for 8,000 time steps, corresponding to 1,000 data assimilation cycle, to examine the performance of adaptive magnitude and the sensitivity of  $D$  for constant magnitude, as shown in Fig. 8. Rate of successful control is calculated as the ratio of cases which NR is controlled in the target regime. Figure 8 (a) shows that rate of successful control for adaptive magnitude was around 97.5 %, suggesting only one case fails out of 40. Total control times by adaptive magnitude without boundary are reduced from those by constant magnitude, when the applied constant magnitudes are smaller than 0.200 (Fig. 8 (b)). Total control times of cases with adaptive  $D$  by growth rate of SV and boundary are larger than those with only adaptive  $D$  by growth rate of SV (blue and magenta lines in Fig. 8 (b)). Experiment with adaptive magnitude by growth rate of SV and boundary achieves the minimal total magnitudes of perturbations, around 90.6, among all experiments in this study (Fig. 8 (c)).

## 5 Conclusions

We investigate the impacts of control on two vectors related to instability, i.e., bred vector and singular vector in the Lorenz-63 model. Results demonstrate that the features of these vectors will change if the state variables are controlled to the target regime. Maximum growth rate of singular vectors shows around 5 % decrease after control, and is introduced to calculate the magnitude of perturbations in control simulation experiment. Accordingly, the manipulation, including total control times and magnitudes of perturbations, is designed to be updated adaptively based on the maximum growth rate of singular vectors. Total control times and magnitudes of perturbations show around 40 % and 20 % reduction, respectively, when updating the magnitude adaptively, which indicates that the manipulations are reduced through the method proposed in this research.



**Figure 8.** Comparison between constant and adaptive magnitudes in terms of (a) Ratio of successful control; (b) Times to control; (c) Total magnitudes. The orange dashed, magenta, and blue lines represent the results of constant  $D$ , adaptive  $D$  by growth rate of SV, and adaptive  $D$  by growth rate of SV and boundary, respectively. Please note that the magenta and blue lines are the results with adaptive  $D$ , which are not dependent on the prescribed  $D$  and are shown as horizontal lines in this figure.

200 Control the state variables of the Lorenz-63 model is a very simplified scenery of meteorological study. For complex dynamic systems, e.g., full-scale numerical weather prediction model, cautions are necessary when apply the proposed method to control the weather. For example, it is difficult to explicitly obtain the tangent linear model in medium and large scale atmospheric models, thus, more studies are necessary on the adaptive manipulation update. Nevertheless, present study towards one step to seek the feasible manipulations in the control simulation experiment. Climate change-*induce* extreme weather, e.g.,  
205 typhoon, storm surge, intensive rainfall, was reported to cause catastrophes in recent years (Kotsuki et al., 2019; Ouyang et al., 2021, 2022). Future research will be focused on exploring the chaotic features by Lyapunov vectors (Ginelli et al., 2007; Tokuda et al., 2019, 2021), and implementing these vectors in atmospheric models to control extreme weather for mitigating natural hazards.

*Code availability.* The code that supports the findings of this study is available from the corresponding authors upon reasonable request.

210 *Data availability.* The authors declare that all data supporting the findings of this study are available within the figures and tables of the paper.

*Author contributions.* MO and SK conceived of the study. SK is the principal investigator. MO conducted the numerical experiments and wrote the manuscript. KT analysed the results. All authors contributed to framing and revising the paper.



*Competing interests.* The authors declare that they have no conflict of interest.

215 *Acknowledgements.* This study was partly supported by JST PRESTO MJPR1924, the Program for Promoting Research on the Super-computer Fugaku of MEXT JPMXP1020200305, the Japan Society for the Promotion of Science (JSPS) KAKENHI grants JP21H04571 JP22K18821, 20K19882, JST Moonshot R&D JPMJMS2284, and the IAAR Research Support Program of Chiba University. The authors thank project members of the Moonshot JPMJMS2284 for fruitful discussion.



## References

- 220 Bishop, C. H., Etherton, B. J., and Majumdar, S. J.: Adaptive sampling with the ensemble transform Kalman filter. Part I: Theoretical aspects, *Monthly Weather Review*, 129, 420–436, [https://doi.org/10.1175/1520-0493\(2001\)129<0420:ASWTET>2.0.CO;2](https://doi.org/10.1175/1520-0493(2001)129<0420:ASWTET>2.0.CO;2), 2001.
- Corazza, M., Kalnay, E., Patil, D. J., Yang, S.-C., Morss, R., Cai, M., Szunyogh, I., Hunt, B. R., and Yorke, J. A.: Use of the breeding technique to estimate the structure of the analysis "errors of the day", *Nonlinear Processes in Geophysics*, 10, 233–243, <https://doi.org/10.5194/npg-10-233-2003>, 2003.
- 225 Diaconescu, E. P. and Laprise, R.: Singular vectors in atmospheric sciences: A review, *Earth-Science Reviews*, 113, 161–175, <https://doi.org/https://doi.org/10.1016/j.earscirev.2012.05.005>, 2012.
- Evans, E., Bhatti, N., Kinney, J., Pann, L., Peña, M., Yang, S.-C., and Kalnay, E.: RISE: Undergraduates find that regime changes in Lorenz's model are predictable, *Bulletin of The American Meteorological Society - BULL AMER METEOROL SOC*, 85, <https://doi.org/10.1175/BAMS-85-4-520>, 2004.
- 230 Ginelli, F., Poggi, P., Turchi, A., Chaté, H., Livi, R., and Politi, A.: Characterizing dynamics with covariant Lyapunov vectors, *Phys. Rev. Lett.*, 99, 130 601, <https://doi.org/10.1103/PhysRevLett.99.130601>, 2007.
- Jolliffe, I. T. and Stephenson, D. B.: *Forecast verification: A practitioner's guide in atmospheric science*, second edition, John Wiley & Sons, Ltd, <https://doi.org/https://doi.org/10.1002/9781119960003>, 2011.
- Kalnay, E., Li, H., Miyoshi, T., Yang, S.-C., and Ballabrera-Poy, J.: 4-D-Var or ensemble Kalman filter?, *Tellus A: Dynamic Meteorology and Oceanography*, 59, 758–773, <https://doi.org/10.1111/j.1600-0870.2007.00261.x>, 2007.
- 235 Kim, H. M. and Jung, B.-J.: Singular vector structure and evolution of a recurving tropical cyclone, *Monthly Weather Review*, 137, 505–524, <https://doi.org/10.1175/2008MWR2643.1>, 2009.
- Kotsuki, S., Terasaki, K., Kanemaru, K., Satoh, M., Kubota, T., and Miyoshi, T.: Predictability of record-breaking rainfall in Japan in July 2018: ensemble forecast experiments with the near-real-time global atmospheric data assimilation system NEXRA, *SOLA*, 15A, 1–7, <https://doi.org/10.2151/sola.15A-001>, 2019.
- 240 Lorenz, E. N.: Deterministic nonperiodic flow, *Journal of Atmospheric Sciences*, 20, 130–141, [https://doi.org/10.1175/1520-0469\(1963\)020<0130:DNF>2.0.CO;2](https://doi.org/10.1175/1520-0469(1963)020<0130:DNF>2.0.CO;2), 1963.
- Lorenz, E. N.: Predictability: a problem partly solved, in: *Seminar on Predictability*, 4-8 September 1995, vol. 1, pp. 1–18, ECMWF, Shinfield Park, Reading, 1996.
- 245 Lucarini, V., Faranda, D., de Freitas, A., de Freitas, J., Holland, M., Kuna, T., Nicol, M., Todd, M., and Vaienti, S.: Extremes and recurrence in dynamical systems, *Pure and Applied Mathematics: A Wiley Series of Texts, Monographs and Tracts*, Wiley, 2016.
- Miyoshi, T. and Sun, Q.: Control simulation experiment with Lorenz's butterfly attractor, *Nonlinear Processes in Geophysics*, 29, 133–139, <https://doi.org/10.5194/npg-29-133-2022>, 2022.
- Norwood, A., Kalnay, E., Ide, K., Yang, S.-C., and Wolfe, C.: Lyapunov, singular and bred vectors in a multi-scale system: an empirical exploration of vectors related to instabilities, *Journal of Physics A: Mathematical and Theoretical*, 46, 254 021, <https://doi.org/10.1088/1751-8113/46/25/254021>, 2013.
- 250 Ouyang, M., Ito, Y., and Tokunaga, T.: Quantifying the inundation impacts of earthquake-induced surface elevation change by hydrological and hydraulic modeling, *Scientific Reports*, 11, 4269, <https://doi.org/10.1038/s41598-021-83309-7>, 2021.
- Ouyang, M., Kotsuki, S., Yuka, I., and Tokunaga, T.: Employment of hydraulic model and social media data for flood hazard assessment in 255 an urban city, *Journal of Hydrology: Regional Studies*, (In print), 2022.





- Palmer, T.: The ECMWF ensemble prediction system: Looking back (more than) 25 years and projecting forward 25 years, *Quarterly Journal of the Royal Meteorological Society*, 145, 12–24, <https://doi.org/https://doi.org/10.1002/qj.3383>, 2019.
- Press, W. H., Teukolsky, S. A., Vetterling, W. T., and Flannery, B. P.: *Numerical recipes in FORTRAN. The art of scientific computing*, 1992.
- 260 Sun, Q., Miyoshi, T., and Richard, S.: Control simulation experiments of extreme events with the Lorenz-96 model, *Nonlinear Processes in Geophysics Discussions*, 2022, 1–18, <https://doi.org/10.5194/npg-2022-12>, 2022.
- Tokuda, K., Katori, Y., and Aihara, K.: Chaotic dynamics as a mechanism of rapid transition of hippocampal local field activity between theta and non-theta states, *Chaos: An Interdisciplinary Journal of Nonlinear Science*, 29, 113 115, <https://doi.org/10.1063/1.5110327>, 2019.
- Tokuda, K., Fujiwara, N., Sudo, A., and Katori, Y.: Chaos may enhance expressivity in cerebellar granular layer, *Neural Networks*, 136, 72–86, <https://doi.org/https://doi.org/10.1016/j.neunet.2020.12.020>, 2021.
- 265 Toth, Z. and Kalnay, E.: Ensemble forecasting at NMC: the generation of perturbations, *Bulletin of the American Meteorological Society*, 74, 2317–2330, [https://doi.org/10.1175/1520-0477\(1993\)074<2317:EFANTG>2.0.CO;2](https://doi.org/10.1175/1520-0477(1993)074<2317:EFANTG>2.0.CO;2), 1993.
- Toth, Z. and Kalnay, E.: Ensemble forecasting at NCEP and the breeding method, *Monthly Weather Review*, 125, 3297–3319, [https://doi.org/10.1175/1520-0493\(1997\)125<3297:EFANAT>2.0.CO;2](https://doi.org/10.1175/1520-0493(1997)125<3297:EFANAT>2.0.CO;2), 1997.
- 270 Yang, S.-C., Kalnay, E., and Hunt, B.: Handling nonlinearity in an ensemble Kalman filter: Experiments with the three-variable Lorenz model, *Monthly Weather Review*, 140, 2628–2646, <https://doi.org/10.1175/MWR-D-11-00313.1>, 2012.
- Zhang, Y., Ide, K., and Kalnay, E.: Bred vectors of the Lorenz63 system, *Advances in Atmospheric Sciences*, 32, 1533–1538, <https://doi.org/10.1007/s00376-015-4275-8>, 2015.